Circuit function		Diversity factor (ks)
Lighting		1
Heating and air conditioning		1
Socket-outlets		0.1 to 0.2 [a]
Lifts and catering hoist [b]	• For the most powerful motor	1
	• For the second most	0.75
	powerful motor	
	• For all motors	0.60

[a] In certain cases, notably in industrial installations, this factor can be higher.
[b] The current to take into consideration is equal to the nominal current of the motor, increased by a third of its starting current

Fig.A14: Diversity factor according to circuit function

Philtex